### Available at Digi-Key\*\* www.digikey.com



2111 Comprehensive Drive Aurora, Illinois 60505 Phone: 630-851-4722 Email: sales@conwin.com www.conwin.com

> DATA SHEET

**Connor Winfield** Delivering a New Generation of Time and Frequency Solutions for a Connected World.

| Bulletin | TM147         |
|----------|---------------|
| Revision | 03            |
| Date     | 22 April 2025 |
|          |               |

# FT9-P Jitter Attenuating Frequency translator



#### Overview

The FT9-P is a small, self-contained frequency translator and jitter attenuator designed to meet requirements for multiple applications where low phase noise and ultra-low jitter outputs are required including: frequency translation supporting wireless communication, 40G,100G and 400G Synchronous Ethernet, OTN and IEEE 1588 network elements, clock translation with low phase noise, and other applications demanding subpicosecond jitter performance.

The FT9-P consists of a PLL stage that attenuates the jitter of the reference input with the use of an integrated phase detector, charge pump and internal VCXO. The FT9-P generates a single-ended LVCMOS 3.3V clock output based on the frequency of the internal VCXO chosen. The FT9-P accepts one reference input from 8kHz to 125MHz, also at



a +3.3V LVCMOS level. The FT9-P can be configured with an internal LVCMOS VCXO from 10MHz to 156.25MHz. The internal disciplined VCXO provides the output characteristics for phase noise and jitter performance for the clock output, which can be further divided down at the output port with 6-bit divider value achieving output frequencies as low as 156.25kHz. This product is based on Connor-Winfield's NF1011 frequency translating IC and is intended to be provided as a factory configured and programmed module for the ease of use and convenience of the user.

#### Features

- Phase locks to an incoming reference input from 8 kHz to 125MHz
- Generates a single ended Low Jitter Clock
  Outputs derived from its internal VCXO
- Status indicators for phase-lock verification and loss of signal (LOS) notification.
- Internal VCXO supports up to 156.25 MHz clock output frequency range
- 3.3VDC Supply Voltage
- -40°C to 105°C operating temperature range
- 9.2 x 9.2mm 16 pin QFN surface mount package

#### Applications

- High Stability Clocking
- Primary Reference Time Clock (PRTC) [G.8272]
- Telecom Grand Master [G.8273.1]
- Telecom boundary clock [G.8273.2]
- Wireless Base Stations
- GNSS Disciplined Oscillator
- NTP Stratum 0 Standard

# **General Description**

The FT9-P module is designed to receive a 3.3V Reference input and generate a frequency-translated single-ended clock output phase locked to the incoming reference input signal.

The PLL consists of an integrated charge pump and phase detector, which locks to an on-board VCXO. The module translates the reference input frequency and attenuates the jitter on the incoming clock signal. The internal VCXO on the FT9-P module provides the output characteristics for phase noise and jitter performance for the clock output.

This module is configured at the factory based on the internal VCXO frequency chosen and requires no additional external components for operation. The model number is configured with an input frequency designator and an output frequency designator.

#### FT9-P Functional Block Diagram



#### Absolute Maximum Ratings

| Parameter                  | Minimum | Nominal | Maximum | Units | Notes |
|----------------------------|---------|---------|---------|-------|-------|
| Power Supply Voltage (Vdd) | -0.3    | -       | 4.0     | Volts |       |
| Storage Temperature        | -55     | -       | 125     | °C    |       |

| Operating Specifications     |         |         |          |        |       |
|------------------------------|---------|---------|----------|--------|-------|
| Parameter                    | Minimum | Nominal | Maximum  | Units  | Notes |
| Input Frequencies            | 8k      | -       | 125.0 M  | Hz     |       |
| Output Frequencies           | 156.25k | -       | 156.25 M | Hz     |       |
| Supply Voltage (Vdd)         | 3.13    | 3.3     | 3.47     | Volts  |       |
| Supply Current               | -       | 80      | 100      | mA     |       |
| REF_IN Voltage               | 2.7     | -       | 3.3      | Vpp    |       |
| Operating Temperature        | -40     | -       | 105      | °C     |       |
| SSB Phase Noise for FT9-P-AB |         |         |          |        |       |
| at 10Hz offset               | -       | -57     | -        | dBc/Hz |       |
| at 100Hz offset              | -       | -92     | -        | dBc/Hz |       |
| at 1kHz offset               | -       | -128    | -        | dBc/Hz |       |
| at 10kHz offset              | -       | -138    | -        | dBc/Hz |       |
| at 100kHz offset             | -       | -150    | -        | dBc/Hz |       |
| at 1MHz offset               | -       | -155    | -        | dBc/Hz |       |
| at 10MHz offset              | -       | -155    | -        | dBc/Hz |       |

### **LVCMOS** Output Characteristics

| Parameter                   | Minimum | Nominal | Maximum | Units | Notes |
|-----------------------------|---------|---------|---------|-------|-------|
| Load                        | -       | 15      | -       | pF    |       |
| Output Voltage              |         |         |         |       |       |
| (High) (Voh)                | 3.0     | -       | -       | V     |       |
| (Low) (Vol)                 | -       | -       | 0.4     |       |       |
| Duty Cycle at 50% of Vcc    | 45      | 50      | 55      | %     |       |
| Rise / Fall Time 10% to 90% | -       | -       | 6       | ns    |       |

### **Environmental Characteristics**

| Vibration:    | Vibration per Mil Std 883E Method 2007.3 Test Condition A                     |
|---------------|---|
| Shock:        | Mechanical Shock per MIL Std 883E Method 2002.4 Test Condition B              |
| Soldering:    | SMD product suitable for Convention Reflow soldering. Peak temperature 260°C. |
|               | Maximum time above 220°C, 60 seconds.   |
| Solderability | Solderability per MIII Std 883E Method 2003. See Solder Profile on Page 4.    |
|               |   |

#### **Package Characteristics**

|                            | i donago onalaotonolioo |  |
|----------------------------|-------------------------|--|
| Package                    | 9.2 x 9.2mm 16 pin QFN  |  |
| Moisture Sensitivity Level | MSL-3                   |  |
|                            |                         |  |



**Delivering a New Generation of Time and** Frequency Solutions for a Connected World.

FT9-P Data Sheet: TM147 Page 2 Rev: 03 Date: 04/22/2025

Specifications subject to change without notification. See Connor-Winfield's website for latest revision. © Copyright 2025 The Connor-Winfield Corporation Not intended for life support applications.

# FT9-P Pin Assignments (Bottom View)



### **FT9-P** Pin Description

| Pin No. | Pin Name | I/O    | Description   |
|---------|----------|--------|---|
| 1       | NC       |        |   |
| 2       | NC       |        |   |
| 3       | NC       |        |   |
| 4       | NC       |        |   |
| 5       | LOS      | 0      | Loss of signal when pin goes HIGH, reference is present when pin is LOW |
| 6       | REF_IN   |        | Reference input. Accepts 3.3V LVCMOS clock signal input                 |
| 7       | NC       |        |   |
| 8       | NC       |        |   |
| 9       | NC       |        |   |
| 10      | NC       |        |   |
| 11      | NC       |        |   |
| 12      | VSS_GND  | Ground | GROUND  |
| 13      | NC       |        |   |
| 14      | LOCK     | 0      | Lock indication when pin goes HIGH, not locked when pin is LOW          |
| 15      | OUTPUT   | 0      | 3.3V LVCMOS Output  |
| 16      | VDD_3.3  | Power  | 3.3V Power Input  |



Delivering a New Generation of Time and Frequency Solutions for a Connected World.

FT9-P Data Sheet: TM147 Page 3 Rev: 03 Date: 04/22/2025

Specifications subject to change without notification. See Connor-Winfield's website for latest revision. © Copyright 2025 The Connor-Winfield Corporation Not intended for life support applications.

#### FT9-P Mechanical Drawing







Dimensional Tolerance: ±0.005 (±0.127mm) unless shown otherwise



Meets IPC/JEDEC J-STD-020C

#### **Output Waveform**





Delivering a New Generation of Time and Frequency Solutions for a Connected World.

#### Suggested Pad Layout



KEEP OUT AREA UNDER THE PCBOARD IS A KEEP OUT AREA, DO NOT PLACE ANY PARTS IN THIS AREA.

FT9-P Data Sheet: TM147 Page 4 Rev: 03 Date: 04/22/2025

Specifications subject to change without notification. See Connor-Winfield's website for latest revision. © Copyright 2025 The Connor-Winfield Corporation Not intended for life support applications.

#### Solder Profile

# **Standard Frequencies**

| 10 MHz     | А |            |   |
|------------|---|------------|---|
| 100 MHz    | В | 65.536 MHz | Т |
| 122.88 MHz | С | 32.768 MHz | W |
| 125 MHz    | D | 64 MHz     | Х |
| 156.25 MHz | E | 38.88 MHz  | Y |
| 80 MHz     | F | 51.84 MHz  | Z |
| 98.304 MHz | G |            |   |
| 61.44 MHz  | Н | 16.384 MHz | 0 |
| 77.76 MHz  | J | 30.72 MHz  | 1 |
| 155.52 MHz | K | 20.48 MHz  | 2 |
| 50 MHz     | L | 5 MHz      | 3 |
| 64 MHz     | М | 12.8 MHz   | 4 |
| 40 MHz     | Ν | 49.152 MHz | 5 |
| 20 MHz     | 0 | 16 MHz     | 6 |
| 25 MHz     | Р | 19.44 MHz  | 7 |
| 96 MHz     | R | 10.24 MHz  | 8 |
| 81.92 MHz  | S | 8 kHz      | 9 |

**Ordering Information** (see standard frequencies listed above) FT9-P - \_ \*\* Not all Models available Input Frequency Output Frequency Example Part Number: FT9-P-AC

> Input Frequency: 10.0 MHz Output Frequency: 122.88 MHz

at Digi-Key

WINFIELD H(~~-

**CONNOR** Delivering a New Generation of Time and Frequency Solutions for a Connected World.

FT9-P Data Sheet: TM147 Page 5 Rev: 03 Date: 04/22/2025



# Marking Configuration



| Revision History |          |   |
|------------------|----------|---|
| Revision         | Date     | Note  |
| 00               | 09/13/23 | New Release   |
| 01               | 12/28/23 | Update photo image, add marking configuration                           |
| 02               | 12/12/24 | Update page 3 pin assignments image to agree with pin description table |
| 03               | 04/22/24 | Update the Supply Current parameter                                     |
|                  |          |   |

2111 Comprehensive Drive Aurora, Illinois 60505 Phone: 630-851-4722 Fax: 630-851-5040 www.conwin.com